

Document made available under the Patent Cooperation Treaty (PCT)

International application number: PCT/IL05/000116

International filing date: 01 February 2005 (01.02.2005)

Document type: Certified copy of priority document

Document details: Country/Office: IL
Number: 160152
Filing date: 01 February 2004 (01.02.2004)

Date of receipt at the International Bureau: 15 March 2005 (15.03.2005)

Remark: Priority document submitted or transmitted to the International Bureau in compliance with Rule 17.1(a) or (b)



World Intellectual Property Organization (WIPO) - Geneva, Switzerland
Organisation Mondiale de la Propriété Intellectuelle (OMPI) - Genève, Suisse





מדינת ישראל
STATE OF ISRAEL

Ministry of Justice
Patent Office

משרד המשפטים
לשכת הפטנטים

This is to certify that
annexed hereto is a true
copy of the documents as
originally deposited with
the patent application
particulars of which are
specified on the first page
of the annex.

זאת לתעודה כי
רצופים בזה העתקים
נכונים של המסמכים
שהופקדו לכתחילה
עם הבקשה לפטנט
לפי הפרטים הרשומים
בעמוד הראשון של
הנספח.



נתאשר
Certified

לשימוש הלשכה
For Office Use

חוק הפטנטים, תשכ"ז - 1967
PATENT LAW 5727 - 1967

ב ק ש ה ל פ ט נ ט
Application For Patent

מספר: Number	160152
תאריך: Date	01-02-2004
הוקדם/נדרחא Ante/Post-dated	

אני, (שם המבקש, מענו ולגבי גוף מאוגד - מקום התאגדותו)
I (Name and address of applicant, and in case of body corporate-(place of incorporation

Rafael-Armament Development Authority Ltd
.P.O.B2250
Haifa31021

רפא"ל - רשות פתוח אמצעי לחימה בע"מ
ת.ד. 2250
חיפה 31021

:InventorMotti Golan, Nitzan Goldberg

ממציא: מוטי גולן, ניצן גולדברג

בעל אמצאה מכח הדין..... Operation of Law שמה הוא
Owner, by virtue of
of an invention the title of which is

עבוד תמונות לסופר רזולוציה


(בעברית)
(Hebrew)

SUPER-RESOLUTION IMAGE PROCESSING

(באנגלית)
(English)

hereby apply for a patent to be granted to me in respect thereof

מבקש בזאת כי ינתן לי עליה פטנט

• בקשת חלוקה - Application of Division		• בקשת פטנט מוסף - Application for Patent Addition		• דרישת דין קדימה Priority Claim		
מבקשת פטנט from Application		לבקשה/לפטנט to Patent/.Appl		מספר/סימן Number/Mark	תאריך Date	מדינת האיגוד Convention Country
מס'..... No..... dated..... מיום		מס'..... No..... dated..... מיום				
יפוי כח: כללי P.O.A.: general/individual-attached/to be filed later- הוגש בענין..... 142994 filed in case.....						
המען למסירת מכתבים בישראל Address for service in Israel .DR. MARK FRIEDMAN LTD BEIT SAMUELOFF 7HAOMANIM STREET 67897TEL AVIV						
חתימת המבקש Signature of Applicant				היום..... 1 בחודש..... Feb שנת..... 2004 of the year..... of This		
				לשימוש הלשכה For Office Use		

..Ref26/604

עבוד תמונות לסופר רזולוציה

SUPER-RESOLUTION IMAGE PROCESSING

Super-Resolution Image Processing

FIELD AND BACKGROUND OF THE INVENTION

The present invention relates to image processing and, in particular, it concerns super-resolution image processing in which a plurality of overlapping
5 sampled images are processed to generate one or more image of resolution and quality greater than that of the original sampled images.

The term "super-resolution" is used to refer generically to a group of techniques through which information from overlapping regions of multiple image frames can be used to improve the resolution of, and reduce noise and
10 blurring in, a resultant image frame. In one super-resolution methodology, described in M. Irani, et al., "Motion Analysis For Image Enhancement Resolution, Occlusion, And Transparency," Jour. Visual Communication And Image Representation, Vol. 4, No. 4, Dec., 1993, pp. 324-335, particularly
15 starting with an initial guess as to an appropriate super-resolution image of a scene, a plurality of low-resolution images are generated and compared to actual low-resolution images which were recorded of the scene. By determining differences between the generated and actual low-resolution images, an error function is developed which is used in updating the initial
20 guess super-resolution image. This process can be repeated through a series of iterations until a final super-resolution image is generated with enhanced resolution over the actual low-resolution images.

An essentially similar approach is also described in a paper by Assaf Zomet and Shmuel Peleg entitled "Efficient Super-Resolution and Application to Mosaics" (Proceedings of the International Conference on Pattern Recognition (ICPR), Barcelona, September 2000). The algorithm in question is there referred to as an "iterative back-projection" algorithm. Both the Irani et al. and Zomet et al. papers are hereby incorporated by reference and are believed to provide an understanding of the theoretical basis and general state of the art against which background the present invention may be better understood.

10 Practical implementations of the iterative back-projection methodology are typically computationally heavy and often suffer from problems of slow convergence, requiring relatively large numbers of iterations to reach an acceptable solution.

There is therefore a need for an implementation of iterative back-projection which would enhance the quality of the resulting super-resolution image and/or would enhance the rate of convergence of the algorithm towards an acceptable solution, thereby reducing the computational load and processing time for performing the super-resolution processing.

SUMMARY OF THE INVENTION

20 The present invention is a method and corresponding image processing system for iterative derivation of a relatively high-resolution master image from a plurality of lower resolution sampled images of non-identical, at least

partially overlapping, regions of a scene. The present invention also provides a technique, useful both alone and as part of the iterative derivation, for combining a plurality of input images into a single higher resolution output image.

5 According to the teachings of the present invention there is provided, a method for iterative derivation of a master image from a plurality of sampled images of non-identical, at least partially overlapping, regions of a scene, the master image having an output resolution greater than a maximum resolution of the sampled images, the method comprising: (a) for each sampled image,
10 defining: (i) a transformation operator F mapping positions within the master image to corresponding positions in the sampled image, (ii) a distortion operator H simulating a modulation transfer function associated with an imaging sensor from which the sampled image was generated, and (iii) a sampling operator D for reducing an image from the output resolution to the
15 resolution of the sampled image; (b) for each sampled image, applying the transformation operator, the distortion operator and the sampling operator to a current master image hypothesis so as to generate a predicted image, and calculating a difference image having pixel values corresponding to the difference in corresponding pixel values between the sampled image and the
20 predicted image; (c) performing back-projection of each of the difference images to generate a correction image for the current master image hypothesis; and (d) employing the correction images to perform a correction to the current master image hypothesis to generate a new master image hypothesis.

According to a first aspect of the present invention, the correction to the current master image hypothesis includes combining the correction images by deriving a weighted average of values of corresponding pixels in the correction images, the weight of each pixel in each correction image being calculated as a function of a distance as measured in the sampled image between: (i) a point in the sampled image to which the pixel in the correction image is mapped by the transformation operator; and (ii) at least one pixel centroid proximal to the point.

According to a further feature of the present invention, the function of a distance is derived from distortion operator H .

According to a further feature of the present invention, distortion operator H corresponds to a combination of a modulation transfer function resulting from an optical system of the imaging sensor and a modulation transfer function resulting from a distortion generated by a sensor element array of the imaging sensor.

According to a second complementary or alternative aspect of the present invention, distortion operator H corresponds to a modulation transfer function describing only a first portion of a distortion generated by the imaging sensor, the method further comprising a post-processing step of deconvoluting a final master image hypothesis to substantially correct a modulation transfer function describing a remainder of a distortion generated by the imaging sensor.

According to a third complementary or alternative aspect of the present invention, the back projection includes employing an operator H^{bp} corresponding to a pseudo-inverse of distortion operator H , wherein H^{bp} approximates to an inverse of H at spatial frequencies below a given value and approaches zero at spatial frequencies above the given value.

According to a further feature of the present invention, the back projection includes employing an operator H^{bp} corresponding to a pseudo-inverse of distortion operator H , wherein H^{bp} is chosen to substantially satisfy the condition: $H^{bp} \times D^t \times D \times H = I$

wherein:

- I is the unit operator for an image of the output resolution;
- D is a sampling operator for reducing an image from the output resolution to the resolution of an input image; and
- D^t is an inflation operator for expanding an image from the resolution of the input image to the output resolution.

There is also provided according to the teachings of the present invention, a method for combining a plurality of input images relating to non-identical but at least partially overlapping regions of a scene to form an output image, the output image having an output resolution greater than a maximum resolution of the input images, the method comprising: (a) defining a mapping between pixel locations in each input image and corresponding positions within the output image; (b) employing the mapping and an interpolation methodology to generate from each input image an output component image at the output

resolution; and (c) combining the output component images by deriving a weighted average of values of corresponding pixels in the output component images, thereby generating the output image, wherein the weight of each pixel in each output component image is calculated as a function of a distance
5 between a point in the input image corresponding to the pixel position in the output component image and at least one adjacent pixel centroid in the input image.

According to a further feature of the present invention, the function of a distance is derived from a modulation transfer function associated with an
10 imaging sensor from which the input images were at least partially derived.

According to a further feature of the present invention, the input images are differential images corresponding to the difference in pixel values between a sampled image and a corresponding predicted image, the predicted images being derived from a previously estimated master image hypothesis, the
15 method further comprising employing the output image to apply a correction to the master image hypothesis.

According to a further feature of the present invention, the function of a distance is derived from a modulation transfer function associated with an imaging sensor from which the input images were at least partially derived.

20 According to a further feature of the present invention, the modulation transfer function is a modulation transfer function corresponding to the distortion generated by a sensor element array of the imaging sensor.

According to a further feature of the present invention, the modulation transfer function is a modulation transfer function corresponding to the distortion generated by the combination of an optical system of the imaging sensor and a sensor element array of the imaging sensor.

5 According to a further feature of the present invention, the interpolation methodology includes employing an operator H^{bp} corresponding to a pseudo-inverse of a modulation transfer function H associated with an imaging sensor from which the input images were at least partially derived, wherein H^{bp} approximates to an inverse of H at spatial frequencies below a given value and
10 approaches zero at spatial frequencies above the given value.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention is herein described, by way of example only, with reference to the accompanying drawings, wherein:

FIG. 1 is a flow diagram of a method according to the teachings of the
15 present invention for iterative derivation of a high-resolution master image from lower resolution sampled images;

FIG. 2 is a schematic illustration of the iterative process performed by the method of Figure 1;

FIGS. 3A and 3B are schematic representations of the sensor array of an
20 imaging sensor and of an associated modulation (distortion) of imaging sensitivity, respectively;

FIG. 3C is a schematic representation of a distortion (point spread function) of an optical arrangement of an imaging sensor;

FIGS. 4A and 4B are schematic representations of a sensor array of an imaging sensor and of the associated current sampled values, respectively;

5 FIG. 4C is an interpolated intensity distribution derived from the samples values of Figure 4B;

FIG. 4D are a corresponding set of high-resolution pixel values produced by transforming and inflating the distribution of Figure 4C;

10 FIG. 4E is a weight function associated with the high-resolution pixel grid where the pixel weight varies as a function of distance of the equivalent point in the original image from the original pixel centroid;

FIG. 5A is a schematic representation of a high-resolution image produced by a combination of two low-resolution images shown schematically in Figures 5B and 5C; and

15 FIG. 6 is a schematic graphic representation of a distortion operator associated with an imaging sensor, the inverse operator and a pseudo-inverse for use in back-projection according to the teachings of the present invention.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

20 The present invention is a method and corresponding image processing system for iterative derivation of a relatively high-resolution master image from a plurality of lower resolution sampled images of non-identical, at least partially overlapping, regions of a scene. The present invention also provides a

technique, useful both alone and as part of the iterative derivation, for combining a plurality of input images into a single higher resolution output image.

5 The principles and operation of systems and methods according to the present invention may be better understood with reference to the drawings and the accompanying description.

Referring now to the drawings, Figure 1 shows a method according to the teachings of the present invention for iterative derivation of a master image from a plurality of sampled images of non-identical, at least partially
10 overlapping, regions of a scene. The method is a "super-resolution" method in the sense that the master image has an output resolution greater than a maximum resolution of the sampled images.

Generally speaking, the method starts by inputting the sampled images (step 10), referred to herein as a vector representation Y_k where k runs from 1
15 to N where N is the number of sampled images to be used. Also input are the imaging sensor properties (step 12), preferably expressed as at least one modulation transfer function (MTF) indicating the distortion of a real scene caused by the camera properties. This MTF is referred to as "distortion operator H ". In certain cases to be discussed below, it is preferred to
20 distinguish between separate components of the overall MTF resulting from (i) the optical arrangement of the imaging sensor and (ii) by the structure of the sensing array within the imaging sensor.

It should be noted that the sampled images Y_k do not necessarily all need to have the same dimensions or resolution, and that each sampled image may have its own corresponding distortion operator. In most common applications, sampled images Y_k are a sequence of images from a single
5 imaging sensor, for example a video camera, and therefore typically have identical pixel dimensions and distortion operators, and similar resolution across a region of interest.

Before proceeding with the iterative processing, it is necessary to define what resolution output image or "master image" is required (step 14). The
10 choice of output resolution along each linear dimension is typically at least about twice the resolution of the sampled images, and may be significantly greater. There is an upper limit, defined by factors including the distortion operator and the number of sampled images available, above which further increase in resolution is no longer helpful. The choice of resolution defines a
15 sampling operator D for reducing an image from the output resolution to the resolution of the corresponding sampled image. Also chosen at this stage is the direction of view to be used for the master image. For simplicity, this is typically chosen to correspond to the viewpoint of one of the sampled images.

Then, at step 16, a transformation operator F is derived for each sampled
20 image. Transformation operator F maps positions within the master image to corresponding positions in the sampled image. The transformation operators are typically derived by performing image feature registration between each sampled image and the reference sampled image chosen to be the view

corresponding to the master image view. This mapping may be a simple mapping of translation, rotation and/or magnification, or may include geometrical warping or other geometrical or pixel-to-pixel mappings to correct for variations in perspective. These mappings are then modified to adjust them to the higher resolution grid of the required master image view.

Having now defined the required terminology, the problem to be solved may be stated as follows. We seek to find a "true" image \underline{X} which, for all values of k from 1 to N satisfies:

$$\underline{Y}_k = \underline{D}_k \underline{H}_k \underline{F}_k \underline{X}$$

An iterative back-projection algorithm can then be defined where, based upon a master image hypothesis \underline{X}_j , the next iterative approximation is given by:

$$\hat{\underline{X}}_{j+1} = \hat{\underline{X}}_j - \underbrace{\sum_{k=1}^N \underline{F}_k^T \underline{H}_k^T \underline{D}_k^T}_{\text{Back projection}} [\underline{Y}_k - \underline{D}_k \underline{H}_k \underline{F}_k \hat{\underline{X}}_j]$$

At step 18, an initial master image hypothesis is generated as a starting point for the iterative processing. Although the iterative processing converges to an acceptable solution substantially independent of the initial hypothesis, it is clearly advantageous to start from a relatively close initial hypothesis. This initial hypothesis may be generated by any of a range of conventional techniques that do not *per se* constitute part of the present invention. More preferably, a mathematical process is used which combines the sampled images

by back-projection and then sums pixels to generate a weighted average in a manner that will be described below.

The iterative processing then begins at step 20 by applying transformation operator **F**, distortion operator **H** and sampling operator **D** to the current master image hypothesis so as to generate a predicted image corresponding to each sampled image, and calculating a difference image having pixel values corresponding to the difference in corresponding pixel values between the sampled image and the predicted image (step 22). On an intuitive level, it will be appreciated that operators **F**, **H** and **D** at least partially model the conditions of the imaging process which generated each sampled image such that, if they were applied to the "true" master image they should produce an image corresponding closely to the corresponding sampled image. Thus, the difference between the predicted image and the sampled image is a measure of the discrepancy between the current master image hypothesis and the true master image.

Then at step 24, each of the difference images undergoes "back-projection". The term "back-projection" is used herein in the description and claims to refer to any process for expanding the difference images to generate a correction image useful for correcting the current master image hypothesis. According to the mathematical analysis proposed by the aforementioned Zomet et al. reference, the back-projection in this case should be implemented by using the transposes of operators **D**, **H** and **F** described above. A preferred

alternative implementation of back-projection according to the teachings of the present invention will be described in detail below.

Finally, at step 26, the correction images are employed to perform a correction to the current master image hypothesis to generate a new master image hypothesis, and the algorithm checks for sufficient convergence. If sufficient convergence of the solution has not yet occurred, the method returns to step 20 or the next iteration. Once sufficient convergence has occurred, the final master image hypothesis is preferably post-processed by de-blurring (step 30 - to be discussed further below) to provide the final master image output.

The stages of this iterative process may be further understood by reference to the example of Figure 2. Specifically, there is shown a current master image hypothesis 32 which is processed by operators D, H, F to generate a column 34 of predicted images. Predicted images 34 are then subtracted pixel-by-pixel from the corresponding sampled images 36 to generate difference images 38. These difference images are then expanded and undergo back-projection to generate correction images (shown combined at 40) which are used as a correction to the current master image hypothesis to generate a new master image hypothesis 42.

Turning now to a more detailed description of the particular distinguishing features of the present invention, these may be subdivided into three different but complementary aspects: (i) implementation of the back-projection methodology of step 24; (ii) variable weighting of pixel values in the correction images for the correction of step 26; and (iii) a simplification of the

iterative process by removing part, or all, of the imaging sensor MTF from the iterative correction process and then correcting the corresponding MTF as part of the separate post-processing step 30. It should be noted that the teachings of the present invention relating to each of these three aspects are believed to be of value independent of each of the other aspects, but that these aspects combine synergistically to provide a particularly effective and efficient overall algorithm. Each of these aspects will now be addressed in turn.

Implementation of Back-Projection Methodology

As mentioned above, the mathematical treatment of Zomet et al. concludes that the "correct" operator to use in the back-projection step is the product of the transposes of operators D, H and F. In other words, they propose performing the back projection step (i.e., from low-resolution difference image to high-resolution correction image) using the transpose of the distortion operator which models the distortion in the forward direction from the "true" high-resolution image to the sampled image. In practice, however, it has been found that convergence of the iterative algorithm using this technique is slow. According to the present invention, this problem is addressed by using an inverse of the distortion operator. The true inverse H^{-1} would theoretically remove distortion much more quickly, but no true inverse exists and an operator closely approximating to the true inverse would greatly increase noise. Instead, the present invention provides a pseudo-inverse, referred to herein as a "back-projection distortion operator" H^{bp} , which provides both relatively rapid conversion of the iteration algorithm and reliable high-quality results. The

forms of the MTF for the distortion operator H , its inverse H^{-1} and a preferred form of the pseudo-inverse H^{bp} are shown graphically in Figure 6. As can be seen, at low spatial frequencies, the pseudo-inverse is essentially identical to the true inverse H^{-1} but decreases at higher frequencies, approaching zero at frequencies where noise levels become problematic.

By way of a non-limiting preferred example of a pseudo-inverse which exhibits the above-stated properties, the pseudo-inverse H^{bp} is chosen to substantially satisfy the condition:

$$H^{bp} \times D' \times D \times H = I$$

wherein:

- I is the unit operator for an image of the output resolution;
- D is a sampling operator for reducing an image from the output resolution to the resolution of an input image; and
- D' is an inflation operator for expanding an image from the resolution of the input image to the output resolution, for example by addition of zeros.

In intuitive terms, the above equation represents an attempt to define an inverse of the distortion operator H after information has been lost by sampling and re-inflation by D and D' , respectively. Since H^{bp} represents a filter and must therefore be independent of position (i.e., it is a linear space invariant ("LSI") operator), all of the rows of the matrix are identical except for a fixed shift. Furthermore, the operator is preferably chosen to be a sparse operator with a pre-chosen fixed number k of parameters (corresponding to the number

of input pixel values which can affect the value of each output pixel), estimation of operator H^{bp} is achieved by estimating k parameters represented by a vector h^{bp} . This allows the above equation to be rewritten as a matrix equation of the form:

5
$$M \times h^{bp} = b$$

where M is a known operator derived from operators D , D^t and H , and b is a known vector derived from I . This set of linear equations can readily be solved by various numerical methods such as, but not limited to, least squares approximation.

10 Variable Pixel Weight in Correction Images

As described earlier, the correction images generated by back-projection step 24 are used to correct the current master image hypothesis in step 26. One conventional approach to performing this correction is by constructing an average of corresponding pixels from all the correction images. In other words, where three correction images overlap at a given pixel, the pixel value total correction value is defined as the average of the values from the corresponding pixels in all three images, such that each correction image contributes with equal weight, providing a third of the pixel value. In a region of a correction image where there is no overlap, the single available pixel value is used
20 unmodified.

It is a particularly preferred feature of certain implementations of the present invention that pixels within each correction image are given differing weights as a function of the geometrical transformation between pixels in the

high-resolution correction images and the corresponding pixel positions in the sampled images. The rationale and a preferred implementation of this approach will now be described with reference to Figures 3A-5C. Parenthetically, it should be noted that this feature is also applicable in other applications where a plurality of input images relating to non-identical but at least partially overlapping regions of a scene have been inflated and interpolated by any interpolation methodology and are combined to form a higher-resolution output image.

Turning now to Figures 3A-3C, it will be appreciated that the distortion MTF of an imaging sensor is typically made up of two principle components. A first component, illustrated schematically as a point-spread function ("PSF") in Figure 3C, results from the properties of the optical arrangement of the imaging sensor. The actual MTF of this component is essentially the Fourier transform of the PSF. A second component of the distortion MTF results from the properties and geometry of the focal-plane sensor array, shown schematically in Figure 3A. These distortions lead to a non-uniform spatial sensitivity of the overall sensor array as illustrated schematically in Figure 3B (each undulation relating to a separate sensor element). As a result, each sensor element is predominantly sensitive to a region of the scene viewed by a central region of the sensor element, and hence the measured pixel values are a better representation of image information at a centroid (geometrical center) of the pixel.

Figures 4A-4D illustrate schematically the implications of this modulated sensitivity in the context of the back-projection or other interpolation process. Specifically, sensor values {6, 4, 9} as measured by three sensor elements in Figure 4A should be considered representative primarily of the sampled image values at positions corresponding to the pixel centroids as shown in Figure 4B. Inflation of this information to the high-resolution format without interpolation would result in zero values inserted between the isolated pixels corresponding to low-resolution pixel centroids. Figure 4C shows schematically the operation of an interpolation methodology, such as application of pseudo-inverse H^{bp} described above, and Figure 4D shows the corresponding digitized image values at the output resolution (in this example, three times greater than the input resolution).

In view of the non-uniform representation of sampled pixels in the output resolution pixels, it is a preferred feature of the present invention that the input images (in this case, the correction images) are combined by deriving a weighted average of values of corresponding pixels in the correction images, where the weight of each pixel in each input image is calculated as a function of a distance as measured in the sampled image between: (i) a point in the sampled image to which the pixel in the correction image is mapped by the transformation operator; and (ii) at least one pixel centroid proximal to the point. In other words, an output image pixel which corresponds closely under mapping by transformation operator F to the centroid of an input image pixel is given a relatively high "weight" factor whereas an output image pixel which

corresponds to a position in the input image more distant from the closest pixel centroid(s) is given a relatively lower "weight" factor. An example of the "weight factor" distribution associated with the output pixel grid of Figure 4D is shown in Figure 4E. Most preferably, the function of distance used to define the weight factors is derived from distortion operator H , and preferably parallels the sensitivity distribution of Figure 3B, shown here as a dotted curve.

The practical implications of the weighted average technique according to the teachings of the present invention are illustrated with reference to Figures 5A-5C. Specifically, Figures 5B and 5C show two low-resolution input images Y_a and Y_b (e.g. sampled images or difference images) to be combined into an output image of linear resolution double the input resolution. In this case, the registration transformation defines the position of Y_a at the top-left corner of the output image and Y_b displaced horizontally therefrom by 3 pixels. The pixels of the output image which map to centroids of the input image pixels are here shown with the pixel values inscribed. The remaining blank pixels contain only interpolated image values (not shown). By using the weight factor distribution of the present invention, it is ensured that the more reliable image information derived from the central region of the input pixels takes precedence over interpolated information from other input images. Thus, the value b_{11} here is substantially unaffected by the interpolated value between a_{21} and a_{31} from the inflated Y_a input image. Where no pixel-center input data is available for a given output pixel (i.e., pixels shown here blank), interpolated values from one or more inflated input images are used.

Simplification of Iterative Processing

As mentioned earlier, the MTF of an imaging sensor is generally made up of two components, a first resulting from the optical system of the imaging sensor and the second resulting from a distortion generated by the sensor element array. In the full solution of the iterative processing described above, the distortion operator H and other elements derived therefrom (e.g. H^{bp}) correspond to the combination of these MTFs. In certain cases, however, particularly where the viewing directions of the sampled images are generally similar, it is possible to further simplification and accelerate the processing of the iterations by removing part, or all, of the imaging sensor MTF from the iterative processing algorithm. By way of one non-limiting example, it has been found effective to subdivide the MTF into its two separate factors and removing the optical MTF from the distortion operator H used in the iterations. In other words, the distortion operator H used corresponds to the MTF resulting from the sensor element array and does not include the MTF resulting from the optical system. The result is that the iterations effectively reconstruct the "true" image modified by the optical MTF distortion. This renders the calculations simpler and leads to faster convergence of the iterations to a final value. In an alternative example, the entire imaging sensor MTF may be removed from the iterative back-projection. In some cases, it is necessary to include some basic interpolation function in place of the omitted operator H . The post-processing step 30 then includes performing deconvolution (deblurring) of the output image to substantially correct distortion resulting

from the optical system MTF. This deconvolution may be performed by any of a number of known deconvolution techniques. The deconvolution process of the post processing is thus rendered very much more efficient since it is performed only once on the final image rather than on each sampled image.

- 5 It will be appreciated that the above descriptions are intended only to serve as examples, and that many other embodiments are possible within the scope of the present invention as defined in the appended claims.

WHAT IS CLAIMED IS:

1. A method for iterative derivation of a master image from a plurality of sampled images of non-identical, at least partially overlapping, regions of a scene, the master image having an output resolution greater than a maximum resolution of the sampled images, the method comprising:

- (a) for each sampled image, defining:
 - (i) a transformation operator F mapping positions within the master image to corresponding positions in the sampled image,
 - (ii) a distortion operator H simulating a modulation transfer function associated with an imaging sensor from which the sampled image was generated, and
 - (iii) a sampling operator D for reducing an image from the output resolution to the resolution of the sampled image;
- (b) for each sampled image, applying said transformation operator, said distortion operator and said sampling operator to a current master image hypothesis so as to generate a predicted image, and calculating a difference image having pixel values corresponding to the difference in corresponding pixel values between the sampled image and the predicted image;
- (c) performing back-projection of each of said difference images to generate a correction image for the current master image hypothesis; and

- (d) employing said correction images to perform a correction to the current master image hypothesis to generate a new master image hypothesis,

wherein said correction to the current master image hypothesis includes combining the correction images by deriving a weighted average of values of corresponding pixels in said correction images, the weight of each pixel in each correction image being calculated as a function of a distance as measured in the sampled image between: (i) a point in the sampled image to which the pixel in the correction image is mapped by the transformation operator; and (ii) at least one pixel centroid proximal to said point.

2. The method of claim 1, wherein said function of a distance is derived from distortion operator H .

3. The method of claim 1, wherein distortion operator H corresponds to a combination of a modulation transfer function resulting from an optical system of the imaging sensor and a modulation transfer function resulting from a distortion generated by a sensor element array of the imaging sensor.

4. The method of claim 1, wherein distortion operator H corresponds to a modulation transfer function describing only a first portion of a distortion generated by the imaging sensor, the method further comprising a post-processing step of deconvoluting a final master image hypothesis to

substantially correct a modulation transfer function describing a remainder of a distortion generated by the imaging sensor.

5. The method of claim 1, wherein said back projection includes employing an operator H^{bp} corresponding to a pseudo-inverse of distortion operator H , wherein H^{bp} approximates to an inverse of H at spatial frequencies below a given value and approaches zero at spatial frequencies above said given value.

6. The method of claim 1, wherein said back projection includes employing an operator H^{bp} corresponding to a pseudo-inverse of distortion operator H , wherein H^{bp} is chosen to substantially satisfy the condition:

$$H^{bp} \times D^t \times D \times H = I$$

wherein:

I is the unit operator for an image of the output resolution;

D is a sampling operator for reducing an image from the output resolution to the resolution of an input image; and

D^t is an inflation operator for expanding an image from the resolution of the input image to the output resolution.

7. A method for iterative derivation of a master image from a plurality of sampled images of non-identical, at least partially overlapping, regions of a scene, the master image having an output resolution greater than a maximum resolution of the sampled images, the method comprising:

- (a) for each sampled image, defining:
 - (i) a transformation operator F mapping positions within the master image to corresponding positions in the sampled image,
 - (ii) a distortion operator H simulating a distortion associated with an imaging sensor from which the sampled image was generated, and
 - (iii) a sampling operator D for reducing an image from the output resolution to the resolution of the sampled image;
- (b) for each sampled image, applying said transformation operator, said distortion operator and said sampling operator to a current master image hypothesis so as to generate a predicted image, and calculating a difference image having pixel values corresponding to the difference in corresponding pixel values between the sampled image and the predicted image;
- (c) performing back-projection of each of said difference images to generate a correction image for the current master image hypothesis; and
- (d) employing said correction images to perform a correction to the current master image hypothesis to generate a new master image hypothesis,

wherein said back projection includes employing an operator H^{bp} corresponding to a pseudo-inverse of distortion operator H , wherein H^{bp}

approximates to an inverse of H at spatial frequencies below a given value and approaches zero at spatial frequencies above said given value.

8. The method of claim 7, wherein H^{bp} is chosen to substantially satisfy the condition:

$$H^{bp} \times D' \times D \times H = I$$

wherein:

I is the unit operator for an image of the output resolution;

D is a sampling operator for reducing an image from the output resolution to the resolution of an input image; and

D' is an inflation operator for expanding an image from the resolution of the input image to the output resolution.

9. The method of claim 7, wherein distortion operator H corresponds to a combination of a modulation transfer function resulting from an optical system of the imaging sensor and a modulation transfer function resulting from a distortion generated by a sensor element array of the imaging sensor.

10. The method of claim 7, wherein distortion operator H corresponds to a modulation transfer function describing only a first portion of a distortion generated by the imaging sensor, the method further comprising a post-processing step of deconvoluting a final master image hypothesis to

substantially correct a modulation transfer function describing a remainder of a distortion generated by the imaging sensor.

11. The method of claim 7, wherein said correction to the current master image hypothesis includes combining the correction images by deriving a weighted average of values of corresponding pixels in said correction images, the weight of each pixel in each correction image being calculated as a function of a distance as measured in the sampled image between: (i) a point in the sampled image to which the pixel in the correction image is mapped by the transformation operator; and (ii) at least one pixel centroid proximal to said point.

12. The method of claim 11, wherein said function of a distance is derived from distortion operator H .

13. A method for iterative derivation of a master image from a plurality of sampled images of non-identical, at least partially overlapping, regions of a scene, the master image having an output resolution greater than a maximum resolution of the sampled images, the method comprising:

- (a) for each sampled image, defining:
 - (i) a transformation operator F mapping positions within the master image to corresponding positions in the sampled image,

- (ii) a distortion operator **H** simulating only a first portion of a distortion generated by an imaging sensor from which the sampled image was generated, and
 - (iii) a sampling operator **D** for reducing an image from the output resolution to the resolution of the sampled image;
- (b) for each sampled image, applying said transformation operator, said distortion operator and said sampling operator to a current master image hypothesis so as to generate a predicted image, and calculating a difference image having pixel values corresponding to the difference in corresponding pixel values between the sampled image and the predicted image;
- (c) performing back-projection of each of said difference images to generate a correction image for the current master image hypothesis;
- (d) employing said correction images to perform a correction to the current master image hypothesis to generate a new master image hypothesis; and
- (e) after performing steps (b) through (d) at least once, deconvoluting a final master image hypothesis to substantially correct a remaining portion of a distortion generated by the imaging sensor from which the sampled image was generated.

14. The method of claim 13, wherein said correction to the current master image hypothesis includes combining the correction images by deriving a weighted average of values of corresponding pixels in said correction images; the weight of each pixel in each correction image being calculated as a function of a distance as measured in the sampled image between: (i) a point in the sampled image to which the pixel in the correction image is mapped by the transformation operator; and (ii) at least one pixel centroid proximal to said point.

15. The method of claim 14, wherein said function of a distance is derived from distortion operator H .

16. The method of claim 13, wherein said back projection includes employing an operator H^{bp} corresponding to a pseudo-inverse of distortion operator H , wherein H^{bp} approximates to an inverse of H at spatial frequencies below a given value and approaches zero at spatial frequencies above said given value.

17. The method of claim 13, wherein said back projection includes employing an operator H^{bp} corresponding to a pseudo-inverse of distortion operator H , wherein H^{bp} is chosen to substantially satisfy the condition:

$$H^{bp} \times D^t \times D \times H = I$$

wherein:

I is the unit operator for an image of the output resolution;

D is a sampling operator for reducing an image from the output resolution to the resolution of an input image; and

D^+ is an inflation operator for expanding an image from the resolution of the input image to the output resolution.

18. A method for combining a plurality of input images relating to non-identical but at least partially overlapping regions of a scene to form an output image, the output image having an output resolution greater than a maximum resolution of the input images, the method comprising:

- (a) defining a mapping between pixel locations in each input image and corresponding positions within the output image;
- (b) employing said mapping and an interpolation methodology to generate from each input image an output component image at the output resolution; and
- (c) combining the output component images by deriving a weighted average of values of corresponding pixels in said output component images, thereby generating the output image,

wherein the weight of each pixel in each output component image is calculated as a function of a distance between a point in the input image corresponding to the pixel position in the output component image and at least one adjacent pixel centroid in the input image.

19. The method of claim 18, wherein said function of a distance is derived from a modulation transfer function associated with an imaging sensor from which the input images were at least partially derived.

20. The method of claim 18, wherein the input images are differential images corresponding to the difference in pixel values between a sampled image and a corresponding predicted image, the predicted images being derived from a previously estimated master image hypothesis, the method further comprising employing the output image to apply a correction to the master image hypothesis.

21. The method of claim 20, wherein said function of a distance is derived from a modulation transfer function associated with an imaging sensor from which the input images were at least partially derived.

22. The method of claim 21, wherein said modulation transfer function is a modulation transfer function corresponding to the distortion generated by a sensor element array of the imaging sensor.

23. The method of claim 21, wherein said modulation transfer function is a modulation transfer function corresponding to the distortion generated by the combination of an optical system of the imaging sensor and a sensor element array of the imaging sensor.

-24. The method of claim 18, wherein said interpolation methodology includes employing an operator H^{bp} corresponding to a pseudo-inverse of a modulation transfer function H associated with an imaging sensor from which the input images were at least partially derived, wherein H^{bp} approximates to an inverse of H at spatial frequencies below a given value and approaches zero at spatial frequencies above said given value.

25. The method of claim 18, wherein said interpolation methodology includes employing an operator H^{bp} corresponding to a pseudo-inverse of a modulation transfer function H associated with an imaging sensor from which the input images were at least partially derived, wherein H^{bp} is chosen to substantially satisfy the condition:


$$H^{bp} \times D^1 \times D \times H = I$$

wherein:

I is the unit operator for an image of the output resolution;


D is a sampling operator for reducing an image from the output resolution to the resolution of an input image; and

D^1 is an inflation operator for expanding an image from the resolution of the input image to the output resolution.


Dr. Mark Friedman Ltd.
Beit Samueloff
7 Haomanim Street
Tel Aviv 67897

by:

FIG. 1






FIG. 3A



FIG. 3B



FIG. 3C




FIG. 4A




FIG. 4B




FIG. 4C




FIG. 4D




FIG. 4E




FIG. 5A





FIG. 5B



y_b




FIG. 5C

FIG. 6

